



“The Source for Power”



## Motorola AN/PRC 153 Charger

**EFB P/N: 1-15100-00**

### **Charger Description**

EFB's Motorola Battery Charger Adapter allows the user to maintain up to 80% charge on a Motorola XTS 5000, 3000 or 2500 Radio in a vest or personal equipment mounted package. The charger may be used as part of the SWIPES™ system or separately powered using the IPS Power Cable, AM/GF (EFB P/N 1-15500-00)

### **Compatible with the following batteries & Power Source**

BA-8180/U, BA-8140/U, ZA-8140S, ZA-8150, IPS HUB, BA-5590/U, BA-5390/U, BA-2590/U, BB-390/U, BB-590/U

### **DC Input**

12 VDC Nominal

### **DC Output**

8.4 VDC Nominal

### **Operational Temperature**

-20°C to +60°C (-4°F to +140°F)

### **Storage Temperature**

-40°C to +100°C (-40°F to +212°F)

### **Dimensions (WxDxL)**

.07 x .064 x .098 Meters (2.75 x 2.50 x 3.88 Inches) Nominal

### **Weight**

.16 kg (0.35 lb) Nominal

### **Environmental**

-Humidity 95%

-Altitude 50,000 ft

Document Number 1-15100-00-SDS

Electric Fuel Battery Corporation, Auburn, Alabama • 1-334-502-9001 • Fax 1-334-502-3008