



“The Source for Power”



Rifleman AN/PRC 154 Charger with Auxiliary Output Cable and with Rifleman Dual Input Dual Output side connector (sidePAN)

EFB P/N: 1-15150-SH

Charger Description

EFB's Rifleman AN/PRC 154 Charger with Auxiliary Output Cable and with Dual Input Dual Output side connector (sidePAN) allows the user to maintain up to 80% charge on an Thales Rifleman Radio charge a EUD and provides an output to exchange data between ab EUD and Radio in a vest or personal equipment mounted package. The charger may be used as part of the SWIPES™ unit or separately powered using the SWIPES™ Power Cable, AM/GF (EFB P/N 1-15500-00)

Compatible with the following batteries & Power Source

BA-8180/U, BA-8140/U, ZA-8140S, ZA-8150, IPS HUB, BA-5590/U, BA-5390/U, BA-2590/U, BB-390/U, BB-590/U

DC Input

12 VDC Nominal

Output

1 Amp 12.6 VDC Maximum

Operational Temperature

-20°C to +60°C (-4°F to +140°F)

Storage Temperature

-40°C to +100°C (-40°F to +212°F)

Dimensions (WxDxL)

.077 x .035 x .096 Meters (3.03 x 2.49 x3.84 Inches) Nominal

Weight

.227 kg (0.498 lb) Nominal

Environmental

-Humidity 95%

-Altitude 50,000 ft

Document Number 1-15150-SH-SDS

Electric Fuel Battery Corporation, Auburn, Alabama • 1-334-502-9001 • Fax 1-334-502-3008