



“The Source for Power”



**AN/PRC-119 (F) ASIP
SINGARS (Foxtrot)
ADAPTER
J-6633/U
NSN: 5940-01-504-3218
EFB P/N: 501230**

Adapter Description

EFB's SINGARS (Foxtrot) Adapter allows the operator to replace the existing battery on an AN/PRC-119 (F) ASIP. The SINGARS (Foxtrot) Adapter used in conjunction with the BA-8180/U will provide approximately 5-9 days of continuous use.

Compatible with the following batteries

BA-8180/U, BA-8140/U, ZA-8125, ZA-8150, BA-5590/U, BA-5390/U, BB-2590/U, BB-390/U, BB-590/U

DC Input

12 VDC Nominal

DC Output

12 VDC Nominal

Operational Temperature

-20°C and 60°C (-4°F and 140°F)

Dimensions

140 mm x 97 mm x 49 mm (5.5" x 3.8" x 1.9")

Weight

0.34 kg (0.76 lb)

Environmental

- Humidity 95%
- Altitude 50,000 ft
- IP67