



“The Source for Power”



**AN/PRC-119 (A-E)
SINGGARS ADAPTOR
J-6634/U
NSN: 5940-01-504-5597
EFB P/N: 501226**

Adapter Description

EFB's SINGGARS Adapter allows the operator to replace the existing battery on an AN/PRC-119 (A-E)

The SINGGARS Adapter used in conjunction with the BA-8180/U will provide approximately 5-9 Days of continuous use.

Compatible with the following batteries

BA-8180/U, BA-8140/U, ZA-8125, ZA-8150, BA-5590/U, BA-5390/U, BB-2590/U, BB-390/U, BB-590/U

DC Input

12 VDC Nominal

DC Output

12 VDC Nominal

Operational Temperature

-20°C and 60°C (-4°F and 140°F)

Dimensions

173 mm x 87 mm x 16 mm (6.8" x 3.4" x 0.6")

Weight

.32 kg (0.71 lb)

Environmental

-Humidity 95%

-Altitude 50,000 ft

-IP67